

# MA-6120MKII/ MA-6240MKII 6-ZONE MIXER AMPLIFIER with Bluetooth / MP3 / FM Tuner

- ❑ Supports MP3/USB/SD/Bluetooth/FM radio function with remote controller and MIC recording function
- ❑ Comes with 4-channel MIC inputs, 2-channel line inputs with individual volume, base and treble control.
- ❑ 6 Zones speaker outputs with individual volume control function
- ❑ Built-in alarm function provides activation to all 6 zones by overriding the BGM
- ❑ Input Priorities: MIC1 > MIC2, MIC3, MIC4, AUX5, AUX6
- ❑ MIC2 to MIC4 built-in 48V phantom power
- ❑ Built-in DC 24V power supply



Technical Specifications

Model	MA-6120MKII	MA-6240MKII
Amplifier Section	120W (RMS)	240W (RMS)
Input sensitivity / Impedance	Mic 1-4: 2.5mV, Line1-2: 250mV	
S/N Ratio (Input)	>70dB	
Frequency Response	80 – 16kHz	
Phantom Power	48V (MIC 2,3,4)	
THD	<0.1%	
Power Supply	AC230V or AC110V, 50-60Hz	
Power Consumption	200W	400W
Weight	9.4kg	10.5kg
Dimensions (W x D x H)	438(W) x 405(D) x 88(H)mm	